



Infiniti Orbital K 4090

HCL recommend Windows® XP Professional for Business

ITEMS	SPECIFICATIONS
Model	Infiniti Orbital K 4090
Chipset	VIA K8M800
Operating System	Preloaded Genuine Windows® XP Home with recovery CD media Preloaded Genuine Windows® XP Professional with recovery CD media Red Hat Linux 4.0 WS
Processor	AMD Athlon 64 (Socket 754) AMD Sempron Processor
BIOS	Flash ROM BIOS
System Memory	DDR 266MHz (PC 2100) /DDR 333MHz(PC 2700)/ 400MHz(PC3200) expandable upto 2 GB, in 2 DIMM slots
Video Graphics	S3 Graphics UniChrome Pro IGP
IDE Channel	2*UDMA 66/100/133 channels upto 4 devices
Hard Disk Drive	2*SATA channels with RAID 0 & 1
Floppy Disk Drive	1.44 MB
Other Devices	Choice of 52x Max-Speed IDE Internal CD ROM Drive, Internal Combo Drive, 52x Internal CD Writer, DVD ROM Drive
Network Interface	Integrated 10/100 Mbps with Wake On LAN
I/O Ports	2*Serial Ports(1 Front+1 Rear), 1* Parallel Port, 8*USB Ports(4 Front+4 Rear),1*RJ45 Port,1*VGA Port,Mic & Audio Ports
Expansion Slots	3* PCI, 1*AGP 8x / 4x
Power Supply	250 Watts & Above
Audio	Integrated 6 Channel Sound
Keyboard & Mouse	Choice of HCL PS/2 Mechanical/Internet/Membrane/Bilingual Keyboard, HCL PS/2 2 Button Scroll /Optical Mouse
Monitors	HCL Digital Color Monitor 15" or above. Choice of CRT & TFT-LCD Monitors
Manageability	HCL Desktop Manageability Software
Multi Level Security	Chassis Intrusion, System Administration/User Boot Password, Serial,Parallel, USB Ports Enable/Disable
Industry Compliance	DMI 2.0, ACPI 1.2